

Inventory: Future Switch x 1 + 12 volt A23 battery x 1 + Instructions

Mounting the FutureSwitch remote switch and fitting the battery





Fig.2

1. To remove cover simply pull the FutureSwitch front and back sections apart at the bottom of the unit where there is a semi circular finger grip.
2. Peel off backing tape (Fig. 2) and position in desired location.
Note: Holes have been provided for optional screw fix mounting (Fig. 1)
3. Whilst the cover is off insert the provided A23 battery (Fig.5) Ensure that the battery is inserted with the correct + and – connections.

Operation




Fig.4

1. Push the top of the FutureSwitch remote wall switch (Fig. 4) to cut the power to all FutureSwitch wall sockets.
2. Push the bottom of the FutureSwitch remote wall switch to put all FutureSwitch wall sockets into power on mode. (red light will appear on the FutureSwitch wall sockets)

Changing the battery




Fig.5

1. Remove cover from the FutureSwitch remote switch as described in section 1 (Mounting the FutureSwitch remote switch and fitting the battery)
2. Remove the old battery and replace with new 12 volt A23 battery.

Adding extra remote switches

1. Turn power off to the FutureSwitch wall socket.
2. Depress the bypass button whilst turning the power on. The bypass button will flash.
3. Push the new FutureSwitch remote switch to pair with your existing wall socket.
4. Wait until the flashing stops or repeat step 3 to pair additional switches.
5. Repeat steps 1 to 4 with all other wall sockets to pair with your new switches.

Specification

- Power Supply FutureSwitch remote switch: 1 x 12 volt type A23 battery
- *Operating distance: 30 meters, works through internal walls and floors.
- Operating frequency: 433.92 MHz

*Operating range may be reduced in some installations, particularly through metallic materials or areas with high electrical interference.

Refer to futurerange.com.au for more complex applications and additional information